# State of Kansas Radio Communications Mutual Aid Reference Guide



This Reference Guide explains the use of the State of Kansas Mutual Aid System.

Public Safety users on any frequency can be connected to other Public Safety users on a different frequency through the mutual aid channel in their radios by a MOTOBRIDGE system installed on Kansas Department of Transportation radio towers.

This Reference Guide gives the procedure to be used to request the connections through Kansas Highway Patrol Central Dispatch.

# State of Kansas Mutual Aid Frequencies Motobridge

800 MHz	Mobile	Repeater	PL Tone	<u>UHF</u>	Mobile	Repeater	NAC
8CALL90	806.0125	851.0125	5A	UCALL40	458.2125	453.2125	5A
8TAC91	806.5125	851.5125	5A	UTAC41	458.4625	453.4625	5A
8TAC92	807.0125	852.0125	5A	UTAC42	458.7125	453.7125	5A
8TAC93	807.5125	852.5125	5A	UTAC43	458.8625	453.8625	5A
8TAC94	808.0125	853.0125	5A				
VHF *				Low Band *			PL Tone
VCALL10	155.7525	155.7525	5A	LCALKS	39.58		5A
VTAC11	151.1375	151.1375	5A	LTACKS	39.70		5A
VTAC12	154.4525	154.4525	5A				
VTAC13	158.7375	158.7375	5A				
VTAC14	159.4725	159.4725	5A				

<sup>\*</sup>Simplex channels only

### **EVENT CHANNELS**

The label is the Troop designation plus the event channel number.


EVENT C2=Troop C, Event Channel 2




## Request for MOTOBRIDGE Channel Assignment

- 1.) Originating caller contacts KHP Dispatch on Radio Call-In channel and identifies their county location.
- 2.) Originating caller requests radio patch to other user. (Caller must provide KHP Dispatch with users TAC bands and locations needing patched together. For example, Shawnee Co. VHF to Shawnee Co. 800.)
- 3.) KHP Dispatch patches the requested channels together through the MOTOBRIDGE console.
- 4.) KHP will then contact the users on the Call-In channels advising them the TAC channels are patched and ready for use.
- 5.) Originating caller completes intended communication with targeted user.
- 6.) Originating caller contacts KHP Dispatch on Radio Call-In channel to cancel the MOTOBRIDGE patch.


### **Northeast Kansas Mutual Aid Channels**




### **Southeast Kansas Mutual Aid Channels**




### North Central Kansas Mutual Aid Channels




## **South Central Kansas Mutual Aid Channels**



### **Northwest Kansas Mutual Aid Channels**




### **Southwest Kansas Mutual Aid Channels**



### Standardized Interoperability Template for 800 MHz P25 Radio System

- The state is divided into 14 zones which correspond with the Homeland Security Regions
- Each zone's talkgroups are set up Identical to correspond with the position of the channel selector on the radio (the first 7 channels are named the same in all zones)
- The channel is named with the region and zone indicator and then the discipline Example: SE1-PSAP is the Southeast Region, Zone 1, PSAP talkgroup
- Use the county listing to find which zone you need to be in to communicate within the appropriate talkgroup, then set your radio to that zone and turn your channel selector knob to get to the correct channel (talkgroup)
- Listing of the channels in each zone:
  - 1 PSAP (Public Safety Answering Point, dispatch centers)
  - 2 MED (Hospitals/Medical)
  - o 3 TAC 1 (regional Tactical talkgroup for all disciplines)
  - o 4 TAC 2 (regional Tactical talkgroup for all disciplines)
  - 5 AES (regional AES encrypted talkgroup for LEO)
  - o 6 KDEM-CALL (hailing talkgroup for KDEM)
  - o 7 NWS (National Weather Service)

# Kansas Homeland Security Regions and KDOT Tower Sites



County	Zone	County	Zone	County	Zone	County	Zone
Allen	SE1	Finney	SW12	Logan	NW14	Rooks	NW13
Anderson	NE4	Ford	SW11	Lyon	NE4	Rush	NW13
Atchison	NE6	Franklin	NE4	Marion	SC9	Russell	NW13
Barber	SC10	Geary	NE5	Marshall	NE6	Saline	NC8
Barton	SC9	Gove	NW14	McPherson	SC9	Scott	SW12
Bourbon	SE1	Graham	NW13	Meade	SW11	Sedgwick	SC10
Brown	NE6	Grant	SW11	Miami	NE4	Seward	SW11
Butler	SC10	Gray	SW11	Mitchell	NC7	Shawnee	NE5
Chase	NE4	Greeley	SW12	Montgomery	SE2	Sheridan	NW14
Chautauqua	SE2	Greenwood	SE2	Morris	NE4	Sherman	NW14
Cherokee	SE1	Hamilton	SW12	Morton	SW11	Smith	NC7
Cheyenne	NW14	Harper	SC10	Nemaha	NE6	Stafford	SC9
Clark	SW11	Harvey	SC9	Neosho	SE1	Stanton	SW11
Clay	NC8	Haskell	SW11	Ness	NW13	Stevens	SW11
Cloud	NC7	Hodgeman	SW11	Norton	NW13	Sumner	SC10
Coffey	NE4	Jackson	NE6	Osage	NE4	Thomas	NW14
Comanche	SC10	Jefferson	NE6	Osborne	NC7	Trego	NW13
Cowley	SC10	Jewell	NC7	Ottawa	NC8	Wabaunsee	NE5
Crawford	SE1	Johnson	KC3	Pawnee	SC9	Wallace	NW14
Decatur	NW14	Kearny	SW12	Phillips	NW13	Washington	NE6
Dickinson	NC8	Kingman	SC10	Pottawatomie	NE6	Wichita	SW12
Doniphan	NE6	Kiowa	SC10	Pratt	SC10	Wilson	SE2
Douglas	NE5	Labette	SE1	Rawlins	NW14	Woodson	SE2
Edwards	SC9	Lane	SW12	Reno	SC9	Wyandotte	KC3
Elk	SE2	Leavenworth	KC3	Republic	NC7		
Ellis	NW13	Lincoln	NC8	Rice	SC9		
Ellsworth	NC8	Linn	NE4	Riley	NE6		

Zone Name	SE1	SE2	КСЗ	NE4	NE5	NE6	NC7	NC8
Channel 1	SE1-PSAP	SE2-PSAP	KC3-PSAP	NE4-PSAP	NE5-PSAP	NE6-PSAP	NC7-PSAP	NC8-PSAP
Channel 2	SE1-MED	SE2-MED	KC3-MED	NE4-MED	NE5-MED	NE6-MED	NC7-MED	NC8-MED
Channel 3	SE1-TAC 1	SE2-TAC 1	KC3-TAC 1	NE4-TAC 1	NE5-TAC 1	NE6-TAC 1	NC7-TAC 1	NC8-TAC 1
Channel 4	SE1-TAC 2	SE2-TAC 2	KC3-TAC 2	NE4-TAC 2	NE5-TAC 2	NE6-TAC 2	NC7-TAC 2	NC8-TAC 2
Channel 5	SE1-AES	SE2-AES	KC3-AES	NE4-AES	NE5-AES	NE6-AES	NC7-AES	NC8-AES
Channel 6	KDEM-CALL							
Channel 7	NWS-ICT	NWS-ICT	NWS-TOP	NWS-TOP	NWS-TOP	NWS-TOP	NWS-GLD	NWS-GLD
Channel 8	H-EVNT-2	H-EVNT-1	A-EVNT-2	A-EVNT-2	B-EVNT-2	B-EVNT-1	C-EVNT-2	C-EVNT-1
Channel 9	H-EVNT-3	H-KHP-1	A-KHP-1	B-EVNT-3	B-EVNT-3	B-EVNT-2	D-EVNT-1	C-EVNT-2
Channel 10	H-KHP-1	H-KHP-2	A-KHP-2	H-EVNT-1	C-EVNT-2	B-EVNT-3	D-EVNT-2	C-EVNT-3
Channel 11	H-KHP-2			H-EVNT-3	B-KHP-2	C-EVNT-2	C-KHP-2	C-KHP-1
Channel 12				A-KHP-1	C-KHP-3	B-KHP-1	D-KHP-1	C-KHP-3
Channel 13				B-KHP-2		C-KHP-2		
Channel 14				C-KHP-3		C-KHP-3		
Channel 15				H-KHP-1				
Channel 16								

Red Talkgroups = Statewide Talkgroups

Purple Talkgroups = KHP Event channels

Zone Name	SC9	SC10	SW11	SW12	NW13	NW14	KDEM/ICS-A	KDEM/ICS-B
Channel 1	SC9-PSAP	SC10-PSAP	SW11-PSAP	SW12-PSAP	NW13-PSAP	NW14-PSAP	KDEM CALL	KDEM CALL
Channel 2	SC9-MED	SC10-MED	SW11-MED	SW12-MED	NW13-MED	NW14-MED	ICS-1	ICS-11
Channel 3	SC9-TAC 1	SC10-TAC 1	SW11-TAC 1	SW12-TAC 1	NW13-TAC 1	NW14-TAC 1	ICS-2	ICS-12
Channel 4	SC9-TAC 2	SC10-TAC 2	SW11-TAC 2	SW12-TAC 2	NW13-TAC 2	NW14-TAC 2	ICS-3	ICS-13
Channel 5	SC9-AES	SC10-AES	SW11-AES	SW12-AES	NW13-AES	NW14-AES	ICS-4	ICS-14
Channel 6	KDEM-CALL	KDEM-CALL	KDEM-CALL	KDEM-CALL	KDEM-CALL	KDEM-CALL	ICS-5	ICS-15
Channel 7	NWS-ICT	NWS-ICT	NWS-DDC	NWS-DDC	NWS-GLD	NWS-GLD	ICS-6	ICS-16
Channel 8	F-EVNT-2	F-EVNT-1	E-EVNT-2	E-EVNT-1	D-EVNT-1	D-EVNT-2	ICS-7	ICS-17
Channel 9	F-EVNT-3	F-EVNT-2	E-EVNT-3	E-KHP-1	D-EVNT-2	D-EVNT-3	ICS-8	ICS-18
Channel 10	YODER	F-EVNT-3	E-KHP-1		D-KHP-1	D-KHP-2	ICS-9	ICS-19
Channel 11	C-KHP-1	YO0DER	E-KHP-2		E-KHP-2		ICS-10	ICS-20
Channel 12	E-KHP-2	E-KHP-2					COMMON-1	COMMON-5
Channel 13	F-KHP-1	F-KHP-1					COMMON-2	COMMON-6
Channel 14	F-KHP-2	F-KHP-2					COMMON-3	COMMON-7
Channel 15	F-METRO-1	F-METRO-1					COMMON-4	COMMON-8
Channel 16							COMU	COMU

Red Talkgroups = Statewide Talkgroups

Purple Talkgroups = KHP Event channels

Zone Name	SOUTH ERT-ICS	NORTH ERT-ICS	M/A 800	M/A 700 *	M/A 700 **	STATE
Channel 1	ICS-1	ICS-11	8CALL90	7CALL50	7CALL70	KTA South
Channel 2	ICS-2	ICS-12	8CALL90 D	7CALL50D	7CALL70D	KTA North
Channel 3	ICS-3	ICS-13	8TAC 91	7TAC51	7TAC71	KTA Event 1
Channel 4	ICS-4	ICS-14	8TAC 91 D	7TAC51D	7TAC71D	KTA Event-2
Channel 5	ICS-5	ICS-15	8TAC 92	7TAC52	7TAC72	KTA Event-3
Channel 6	ICS-6	ICS-16	8TAC 92 D	7TAC52D	7TACZ2D	SFM INV-1
Channel 7	ICS-7	ICS-17	8TAC 93	7TAC53	7TAC73	SFM HZM-1
Channel 8	ICS-8	ICS-18	8TAC 93 D	7TAC53D	7TAC73D	SFM SAR-1
Channel 9	ICS-9	ICS-19	8TAC 94	7TAC54	7TAC74	SFM CMD-1
Channel 10	ICS-10	ICS-20	8TAC 94 D	7TAC54D	7TAC74D	SFM TAC-1
Channel 11	COMMON-1	COMMON-5		7TAC55	7TAC75	W&P Evt 1
Channel 12	COMMON-2	COMMON-6		7TAC55D	7TAC75D	W&P Evt 2
Channel 13	COMMON-3	COMMON-7		7TAC56	7TAC76	W&P Evt 3
Channel 14	COMMON-4	COMMON-8		7TAC56D	7TAC76D	W&P Evt 4
Channel 15	СОМИ	СОМИ				W&P Evt 5
Channel 16						MERG-4

Red Talkgroups = Statewide Talkgroups

Purple Talkgroups = KHP Event channels